



# eduroam

## Web Interface User Guide

# Contents

<a href="#">Introduction</a>	3
<a href="#">Login Page</a>	3
<a href="#">Main Page</a>	4
<a href="#">Managing your Radius Servers</a>	5
<a href="#">Managing your Realms</a>	8
<a href="#">Managing the Test Users</a>	10
<a href="#">Managing the Access Points</a>	12
<a href="#">Information about the Belnet Radius servers.</a>	15
<a href="#">Managing your Password</a>	15

# Eduroam Web Interface User Guide

## Introduction

The online registration service enables you to simplify the management of your radius servers, your realms (domains) and some administrative information associated with the eduroam service.

This document is a user guide which will enable you to use this new tool by showing you the different stages and different elements that you can provide and manage for this service.

## Login Page


Simply go to the <https://register.eduroam.be> page. The first page which is displayed is the Belnet services login page.

Enter your user name and your password.

Your user name has the form **your\_lastname\_firstname@yourinstitution.be**

If you do not know your password or this is the first time you are logging in, you can follow the procedure for changing or resetting your password.

**Note** that you can only access the system if you have gone through the administrative procedure for subscribing to the service.



## Main Page

**Belnet**  
dedicated connectivity

### Belnet Eduroam Register Service

**BELNET Eduroam Register Service**

Help: philippe@belnet.be

**You will be able to manage all information related to your eduroam configuration**

- Radiuses 2 (radius servers) defined please click here to manage your radius servers
- Radiuses 2 realms (domains) defined please click here to manage your realms (domains)
- Radiuses 1 location defined please click here to manage your location
- Radiuses 1 test users defined click here to manage your test users

Information related to your eduroam results can be found still in <http://www.eduroam.be> if you want to change. Please click here

©2013 Belnet - 1 rue Samart - Gand

belspo.be

As you can see on the above screen, the site is composed of two parts. The left-hand part includes a menu allowing you access to specific information. The right-hand part will display the information about the menu.

After you have been authenticated on the site, the right-hand part of the page will contain a summary of the information that you have sent to us.


It is also on this page that you can modify the URL providing information on the implementation of eduroam in your institution, by clicking on the link.

The menu contains 7 items

- **Your radius servers:** allows you to specify the different settings for your radius servers which will be connected to Belnet's radius servers.
- **Your realms:** allows you to define the realms (domains) for which eduroam will be configured.
- **Your location:** allows you to set the eduroam locations or access points which are available in your institution, as well as information relating to these access points.
- **Your test users:** allows you to define the information for one or more test users. These will allow you to carry out tests during the configuration phase and to establish monitoring of the Belgian node.
- **Belnet Radius:** in this section you will find all the information (IP address, Belnet test user) allowing you to connect your radius servers to Belnet's radius servers.
- **Password:** allows you to manage your user name and password.
- **Home:** takes you back to the home page.

## Managing your Radius Servers


The first time that you click on the **Your radius servers** menu the following screen is displayed:



The screenshot shows the Belnet Eduroam Register Service web interface. The header includes the Belnet logo and the text 'dedicated connectivity'. The main title is 'Belnet Eduroam Register Service'. On the left, there is a navigation menu with options: Home, Your radius servers, Your realms, Your locations, Your last users, RADIUS Radius, Admin (with sub-options: Validate, Manage data), and Password. Below the menu, the user's name 'Philippe Van Hecke' and email 'philippe@belnet.be' are displayed. The main content area is titled 'List of configured radius servers' and contains the text 'Click here to add new radius server' with an 'Add' button. At the bottom, there is a footer with '© 2017 Belnet - Disclaimer - Contact' and the 'belspo.be' logo.

The right-hand side of the screen prompts you to enter the information about your first radius server. Press the **Add** button.

A new screen is displayed with a form.



The screenshot shows the 'Add radius servers' form in the Belnet Eduroam Register Service web interface. The header and navigation menu are the same as in the previous screenshot. The main content area is titled 'Add radius servers' and contains a list of instructions: 'Not a valid IPv4 public address', 'please provide a valid public IP address', 'Should be seen as Belnet public view. Be you need to turn on your proxy config', and 'Should be seen as Belnet private view. Be you need to turn on your proxy config'. The form fields are: 'IP address' (0.0.0.0), 'Auth port' (379), 'Account port' (379), 'Client shared secret' (c1pDR8qUJ29p75H7.0xM.usCG5), 'Proxy shared secret' (m1.707ms.42Rk2D5-RK0sV4d90E), 'Priority' (5), and 'So only' (checked). There is an 'Add' button at the bottom.

This form contains the following fields:

- **IP address:** in this field, you must enter your radius server's IP address. This address must be a valid public IP address.
- **Auth port:** in this field, you must enter the UDP port used for authentication. The standard ports are normally ports 1812 and 1645.
- **Account port:** in this field, you must enter the UDP port used for accounting. The standard ports are normally ports 1813 and 1646.
- **Client shared secret:** in this field, you must provide the shared key which will be used by your radius server when it contacts our radius servers. You must use this key in the proxy part of the configuration of your radius server. This shared key must have a minimum length of 8 characters and a maximum length of 31 characters. It must contain a set of alphanumeric characters, a mixture of characters in upper and lower case and a certain number of symbols such as '&!@ ...'.
- **Proxy shared secret:** in this field, you must provide the shared key which will be used by our radius servers when they contact your radius server. You must use this key in the **Client** part of the configuration of your radius server. This shared key must have a minimum length of 8 characters and a maximum length of 31 characters. It must contain a set of alphanumeric characters, a mixture of characters in upper and lower case and a certain number of symbols such as '&!@ ...'.
- **Priority:** where you have several radius servers, this field contains the order in which our radius servers will contact yours. The radius server with the lowest priority will be contacted first.
- **Sp only:** if you have joined eduroam as a service provider only, activate this field.


When all the fields are filled in, and then simply click on the **Add** button. If all the fields are not filled in correctly, the form is redisplayed and the fields filled in incorrectly are displayed with information indicating the error that you have made.

If the form has been properly completed, the page containing a summary of the information as well as the processing status of the server you have added is displayed.



## Managing your Realms

When you click the **Your realms** menu, the realms management page is displayed on the right-hand part.



This information page includes several tables containing the list of realms currently configured for your institution.

Valid and active realms will be shown in the **List of valid and active realms** table. These realms are configured to operate with Belnet's radius servers.

The realms that you have disabled are listed in the **List of disabled and non-active realms** table. These realms are no longer configured to operate with Belnet's radius servers but are still registered.

**Note** that all changes to information in relation to your realms must be validated by our technical team.

Realms awaiting validation from us are listed in the **List of realms awaiting validation** table.

If the list of realms is empty, you will be asked directly if you wish to add a new realm. In this case, simply click on the **Add** button present on the right-hand side of the page.

From this page, you can manage all your realms using the action list and the **Execute** button.

The actions that you can perform on your realms are the following:

- **Edit**: this action allows you to modify your realms
- **Add**: allows you to add a new realm
- **Disable**: allows you to disable temporarily a realm
- **Enable**: allows you to re-enable a previously disabled realm
- **Delete**: allows you to delete a realm

Once the action has been chosen, simply press the **Execute** button for it to be executed. Only the previously selected realm (**Selected** column) will be concerned by the action.

To add a new realm, simply execute the **Add** action. The following screen appears asking you to enter your realm.

In the **Name** field, enter the realm name in the form **your\_institution.be** form.







If you have more than one realm associated with the eduroam service, it is preferable to have one test user per realm.

## Managing the Access Points

The information about the location of access points is not mandatory. The aim is to be able to fill in a Google map which summarises the locations where eduroam access is available (see [http://monitor.eduroam.org/eduroam\\_map.php?kml=europe\\_capital](http://monitor.eduroam.org/eduroam_map.php?kml=europe_capital) )

By clicking on the **Your location** link the following page is displayed:

Belnet  
dedicated connectivity

Belnet Eduroam Register Service

List of eduroam enabled locations

Are you confident that all your eduroam enabled location

Street	Box	City	Zip Code	Access Point	Auth Mechanism	Selected
Avenue Louis Pasteur	1000	Brussels	1050	40	WPA2-Enterprise	Selected

Add Edit Execute

Philippe Van Hecke  
(philippe@belnet.be)

This information page includes a table containing the list of locations with eduroam access currently configured for your institution.

If the list is empty, you will be asked directly if you wish to add a new location. In this case, simply click on the **Add** button present on the right-hand side of the page.

From this page, you can manage all the access locations using the action list and the **Execute** button.

The actions that you can perform on your access locations are the following:

- **Edit**: this action allows you to modify the information for an access location
- **Add**: allows you to add a new access location
- **Delete**: allows you to delete an access location

Once the action has been chosen, simply press the **Execute** button for it to be executed. Only the previously selected location (**Selected** column) will be concerned by the action.

To add a new location, simply execute the **Add** action. The following screen appears asking you to enter the information about the location.

**Belnet** dedicated connectivity

Belnet Eduroam Register Service

**Modify location**

Street:

City:

Box:

Zipcode:

Latitude:  Latitude: Latitude (Latitude and longitude) on Google Maps

Longitude:  Longitude: Longitude (Latitude and longitude) on Google Maps

Number of Access point:

Access method:

- WPA2-PSK
- WPA2-ES
- WPA2-TEAP
- WPA2-0015


Access point:

The following information should be entered into this form:

- **Street:** the street in which is the access point(s) is (are) located.
- **City:** the municipality in which the street is located.
- **Box:** the number in the street.
- **Zipcode:** the postcode associated with the municipality.
- **Latitude** and **longitude:** correspond to the coordinates for geolocation on a Google map. If you do not know these coordinates, the application will try to define them on the basis of the Street, City, Box, ZipCode information using Google's API. You can obtain these coordinates yourself using the Google Maps site.



After having entered your address, a point corresponding to your address appears on the map. By clicking on this point with the right button of your mouse, a menu is displayed allowing you to display the coordinates on the map.



The first figure corresponds to the latitude and the second to the longitude. These are the figures that you must enter.

- **Number of access points:** number of WiFi access points at the location
- **Auth method:** type of security associated with the WiFi access points


- **Description:** a simple description or comment

## Information about the Belnet Radius servers.

By clicking on **Belnet Radius** you will find information about Belnet's radius servers and the information associated with a test user in the 'Belnet.be' realm. This information will allow you to configure your servers properly and to carry out tests.

## Managing your Password

By clicking on **Password**, the page for managing your password is displayed.



This page allows you to either **change your password**, or renew it if you have forgotten it. You simply need to follow the instructions which will be provided by clicking on the associated link.